

AUDIO EXTENDER



(Local)



(Remote)

(AUDIO-E)

Features

- The extension of audio stereo and microphone up to 300 meter away by using the Audio Extender and one CAT5 cable.
- Audio Out supports multimedia speakers and Headphones or Earphones.
- Mic In supports Condenser Microphone and Dynamic Microphone.
- Built-in Microphone preamplifier.
- Microphone gain can be adjustable.

Specifications

| Function | Audio-L | Audio-R |
|------------------------|---|---------|
| Audio Out/In Connector | 1x 3.5mm | |
| Mic In/Out Connector | 1x 3.5mm | |
| RJ-45 Connector | 1 | |
| Frequency response | 10 Hz to 25 KHz /-3dB (1Vp-p/10k Ohms) | |
| Audio In impedance | 10k Ohms | |
| MAX. Audio Input level | 1.8Vp-p | |
| MAX. Mic Input level | 0.5Vp-p | |
| MAX. Mic gain | 0 to +15dB | |
| Cable Distance | 300 m (Max.) | |
| Power Adapter (Min.) | DC 9V 300mA | |
| Housing | Metal | |
| Weight | 65 g | 66 g |
| Dimensions (LxWxH) mm | 92x34x22 | |

LOCAL FRONT VIEW



1. Power jack (DC 9V/300mA)
2. CAT.5 (RJ-45 Connector)

LOCAL REAR VIEW



1. Audio In
2. Mic Out

REMOTE FRONT VIEW



1. Power LED
2. CAT.5 (RJ-45 Connector)

REMOTE REAR VIEW



1. Audio Out
2. Mic In

USER MANUAL

Package Contents-

- Audio Extender Local Unit
- Audio Extender Remote Unit
- 1 user manual
- 1 power adapter DC 9V/300mA
- 1 Smart View custom cable (2L-1218C)

Any thing missed, please contact with your vendor.

REMOTE BOTTOM VIEW



1. Microphone gain adjust

Installation

1. Turn off the PC.
2. Connect AUDIO-E Local Unit Audio and Mic with 3.5mm plug cable from PC.
3. Connect the AUDIO-E Local and Remote Unit with CAT.5 cable.
4. Connect the Headphones and Microphone plug into the AUDIO-E Remote Unit.
5. Connect the power cord.
6. Turn on the PC and play music.

Additional Options

Select any additional options you may require.

1. 6.3mm to 3.5mm Microphone plug adapter.
(Item No: AD3262)




2. RCA to 3.5mm Audio plug adapter.
(Item No: AD320RJ)



Wiring Information & Coding

| Conductor Identification | RJ45 Pin Assignment | Color Code for Conductor |
|--------------------------|---------------------|--------------------------|
| Pair 1 | 5 | White-Blue |
| | 4 | Blue |
| Pair 2 | 1 | White-Orange |
| | 2 | Orange |
| Pair 3 | 3 | White-Green |
| | 6 | Green |
| Pair 4 | 7 | White-Brown |
| | 8 | Brown |



© C&C TECHNIC TAIWAN CO., LTD. All rights reserved.

Trademarks:

All the companies, brand names, and product names referred to this manual are the trademarks or registered trademarks belonging to their respective companies.